

200W GaN PD **Charger** with Charging Display



Single charging port: USB-C1, USB-C2 & USB-C3: up to 100W USB-A1 & USB-A2: up to 22.5W

Part# AC-PW1Y11-S1

With GaN² Pro technology allows you to fast charge and protect 3 USB-C and 2 USB-A powered devices simultaneously, and with LED digital display provides charging status in real time



USB-A charging

- Comes with 3 USB-C and 2 USB-A charging ports to fully charge your power devices such as laptop, smartphone, table, earphone... simultaneously for best power charging efficiency
- This 200W GaN PD Charger with Charging Display provides a total 200W power output - Max. 3x USB-C 100W (USB-C 1, 2, & 3), and 2x USB-A 22.5W (USB-A 1 & 2) and display voltage and current charging data of each port
- The new Gallium Nitride 2 (GaN²) Pro semiconductor material achieve low heat temperature, higher charging efficiency, hard, and smaller size. Allows operation at higher voltages and switching frequencies, is more powerful and durable, and offers multiple protections to protect your devices from Over-Current, Short-Circuit, and Over-Voltage
- Three USB-C ports are compatible with Power Delivery 3.0, Fast Charging 2.0, and Programmable Power Supply (PPS) protocol technology, and two USB-A port are compatible with Quick Charger 3.0 (QC 3.0) protocol technology

Common Applications

• Office, Home, Workstation, Hotel, Coffee shop, Airport, Travel, Library, Restaurant

charging



Automatic Adjustment Power Deliver

1-Port	3-Port
USB-C1	USB-C1+C2+C3
100W	100W+65W+30W
USB-C2	USB-C1+C2+(USB-A1/A2)
100W	100W+65W+22.5W
USB-C3	USB-C1+C3+(USB-A1/A2)
100W	100W+65W+22.5W
USB-A1	USB-C2+C3+(USB-A1/A2)
22.5W	100W+65W+22.5W
USB-A2	(USB-C1/C2/C3)+USB-A1+USB-A2
22.5W	100W+7.5W+7.5W
2-Port	4-Port
USB-C1+C2	USB-C1+C2+C3+(USB-A1/A2)
100W+100W	100W+65W+20W+15W
USB-C1+C3	USB-C1+C2+USB-A1+A2
100W+100W	100W+65W+7.5W+7.5W
USB-C2+C3	USB-C1+C3+USB-A1+A2
100W+100W	100W+65W+7.5W+7.5W
USB-A1+A2	USB-C2+C3+USB-A1+A2
12W+12W	100W+65W+7.5W+7.5W
(USB-C1/C2/C3)+USB-A1 100W+22.5W	5-Port
(USB-C1/C2/C3)+USB-A2	USB-C1+C2+C3+USB-A1+A2
100W+22.5W	100W+65W+20W+7.5W+7.5W



www.siig.com