



2x1 DisplayPort 4K KVM USB 3.0 Switch with Remote Control



IR remote control included

*Video resolution
up to 8K@30Hz*

Part# CE-KV0C11-S1

Easily control/switch 2 DisplayPort computers to 1 DisplayPort/HDMI display via one set of keyboard & mouse



- Allows you to control 2 DisplayPort computers and switch a DisplayPort or HDMI display / monitor with one set of keyboard & mouse to boost multitask efficiency
- Supports video resolution up to 8K (7680x4320)@30Hz with DisplayPort 1.4 or 4K (3840x2160)@60Hz with DisplayPort 1.2 / HDMI, 3D, Deep color
- Features two DisplayPort and USB 3.2 Gen 1 Type-B input ports, one HDMI video output port, one DisplayPort video output port, two USB 3.2 Gen 1 Type-A ports, two USB 2.0 Type A ports, four 3.5mm stereo audio jacks, four 3.5mm microphone jacks, one Infrared (IR) jack, two switch buttons, one power on/off button, and one DC 5V/3A power jack
- Provides two USB 3.2 Gen 1 Type-A ports to connect multiple peripherals, up to 5Gbps data transfer rate and two USB 2.0 Type-A ports for independent HID keyboard & mouse
- Easily switch between computer/device via the front panel push buttons, USB keyboard hotkeys, or IR remote control make this 2x1 DisplayPort 4K KVM USB 3.0 Switch with Remote Control user-friendly to operate
- Plug-n-play. Automatic screen scan, EDID passthrough, no driver installation required

Common Applications

- Media editing, Photo shooting studio, Audio/Video presentation room, Educational facilities, Office, Workstation, Medical office, Control center, Server room, Testing lab

Single
View

KVM

DP
HDMI

8K/4K

USB