



4x1 DisplayPort 4K KVM USB 3.0 Switch with Remote Control



IR remote control included →

Video resolution up to 8K@30Hz

Part# CE-KV0D11-S1

Easily control/switch 4 DisplayPort computers to 1 DisplayPort/HDMI display via one set of keyboard & mouse



Front view



Back view



- Allows you to control 4 DisplayPort computers and switch a DisplayPort or HDMI display/monitor, USB, and audio with one set of keyboard & mouse to boost multitask efficiency
- Supports video resolution up to 8K (7680x4320)@30Hz with DisplayPort 1.4 or 4K (3840x2160)@60Hz with DisplayPort 1.2 / HDMI, 3D, Deep color
- Features four DisplayPort and USB 3.2 Gen 1 Type-B input ports, one HDMI video output port, one DisplayPort video output port, two USB 3.2 Gen 1 Type-A ports, two USB 2.0 Type A ports, six 3.5mm stereo audio jacks, six 3.5mm microphone jacks, one Infrared (IR) jack, four switch buttons, one power on/off button, and one DC 5V/3A power jack
- Provides two USB 3.2 Gen 1 Type-A ports to connect multiple peripherals, up to 5Gbps data transfer rate and two USB 2.0 Type-A ports for independent HID keyboard & mouse
- Easily switch between computer/device via the front panel push buttons, USB keyboard hotkeys, or IR remote control make this 4x1 DisplayPort 4K KVM USB 3.0 Switch with Remote Control user-friendly to operate
- Plug-n-play. Automatic screen scan, EDID passthrough, no driver installation required

Common Applications

- Media editing, Photo shooting studio, Audio/Video presentation room, Educational facilities, Office, Workstation, Hotel, Medical office, Control center, Server room, Testing lab

Single View

KVM

DP HDMI

8K/4K

USB