



4x1 HDMI 4K HDR KVM USB 3.0 Switch with Remote Control



IR remote control included →

Video bandwidth
up to 18Gbps

Part# CE-KV0F11-S1

*Easily control/switch 4 HDMI computers
to 1 HDMI display via one set of keyboard
& mouse for increased productivity*



Front view



Back view



- Allows you to control 4 HDMI computers and switch a HDMI display/monitor with one set of keyboard & mouse
- Supports video resolution up to 4K (3840x2160)@60Hz, HDR, HDCP 2.2, 3D, and Deep color
- Features four HDMI and USB 3.2 Gen 1 Type-B input ports, one HDMI video output port, two USB 3.2 Gen 1 Type-A ports, two USB 2.0 Type A ports, six 3.5mm stereo audio jacks, six 3.5mm microphone jacks, one Infrared (IR) jack, two switch buttons, one power on/off button, and one DC 5V/3A power jack
- Provides two USB 3.2 Gen 1 Type-A ports to connect multiple peripherals, up to 5Gbps data transfer rate and two USB 2.0 Type-A ports for independent HID keyboard & mouse
- Easily switch between computer/device via the front panel push buttons, USB keyboard hotkeys, or IR remote control make this 4x1 HDMI 4K HDR KVM USB 3.0 Switch with Remote Control user-friendly to operate
- Plug-n-play. Automatic screen scan, EDID passthrough, no driver installation required

Common Applications

- Media editing, Photo shooting studio, Audio/Video presentation room, Educational facilities, Office, Workstation, Medical office, Control center, Server room, Testing lab, Hotel

Single
View

KVM

HDMI

4K
60Hz

USB