




8x8 HDMI 4K60Hz Matrix Switcher



HDMI data transfer rate
up to 18Gbps

Part# CE-MX0011-S1

Easily control and switch 8 audio/video to 8 displays, with audio embedded, audio extraction, and auto downscaling function to create a 4K60Hz powerfule matrix solution



- Allows any of the 8 HDMI sources to be displayed on any of the 8 HDMI displays and simultaneously share the same content or select individual content on each display
- Supports UHD video resolution up to 4K (3840x2160)@60Hz, HDR 10, HDCP 2.2, YUV 4:4:4 8-bit, full 3D, HLG, Dolby vision
- Features eight HDMI video input, eight HDMI video output, eight 3.5mm stereo audio input, eight 3.5mm stereo audio output, eight S/PDIF (Coaxial) audio output, one RJ-45 network, one RS-232 control, one IR extend, one grounding, one LCD screen for real-time connection status, eight input buttons, eight output buttons, and six function buttons (Preset/Up/Lock/Menu/Down/Enter)
- Supports HDMI downscaling from 4K@60Hz to 1080p@60Hz and EDID management
- Supports analog audio embedded. Audio extraction via S/PDIF (Coaxial) output and HDMI output with Audio Return Channel (ARC) function
- This Matrix switcher can switch every output channels from any HDMI input via front pannel push buttons, IR remote control, RS-232 command, and Web GUI control
- Easy installation with 1U 19 inch standard rack mount ears. CEC supported

Common Applications

- Security center, Control center, Surveillance control center, Military command, Exhibition, Retail store, Chain store, Shopping center, Digital signage, Classroom, Hospital, Restaurant, Server room, Airport

